



INTERCOSMO 1000

FULL-DUPLEX WIRELESS INTERCOM 1000FT SUPPORT WIRELESS TALLY

THE WIRELESS INTERCOM SYSTEM CONTAINS 1 BASE STATION, SUPPORTS UP TO 8 BELT PACKS AND WIRELESS TALLY FUNCTION. THE SYSTEM CAN SEAMLESSLY COMMUNICATE WITH THE VOICE AND TALLY PORTS OF THE UNIVERSAL SWITCHER.

Features

- Full-duplex Wireless Communication, 1000ft
- 1.9GHz Frequency Band
- 4 External Antennas
- Wireless and Wired Tally
- Base Station x Max 8 Beltpack

- DC/AC Dual Power Supply System
- · LCD Screen, easy to operate
- USB upgrade

Packing List



AC Power Cable:1pcs

High Gain Antenna:6pcs

Gooseneck Microphone:1pcs

User Manual:1pcs

Spec

| | Base Station | Beltpack |
|----------------------|---|--|
| Interface | Antenna Interface x 4 2—wire audio input and output interface x 2 25PIN Tally input interface DC IN ,AC IN USB interface Goose neck interface 3.5mm audio interface | Wireless interface x 2 3.5mm audio interface 3.5mm Tally output interface Mini USB interface |
| Power Supply Range | 12V DC & 110-240V AC | 3 AA Batteries |
| Power Consumption | <1.5W | <0.4w |
| Size | 482.6x175x44.4mm | 108x65x25mm |
| Frequency Band | 1.9GHz | 1.9GHz |
| Modulation Mode | GFSK | GFSK |
| Transmission Power | Max 24dBm | Max 24dBm |
| Receiver Sensitivity | -92dBm | -92dBm |
| Bandwidth | 1.7MHz | 1.7MHz |